

Power Management Options	
POWER MANAGEMENT	ON
SERIAL PORTS	ENABLED
HARD DISK TIMEOUT	1 Minute
DISPLAY TIMEOUT	28 Minutes
STANDBY MODE TIMEOUT	Never Timeout
RESUME MODE	OFF
SUSPEND TIMEOUT	Never Timeout

ESC TO QUIT, F1 TO UPDATE	USE UP/DOWN ARROWS TO MOVE USE LEFT/RIGHT ARROWSTO CHANGE
------------------------------	--

Using the POWER383 Utility:

The power program (Power383) lets you temporarily change the power-management parameters without restarting the computer. These parameters let you do the following:

- * Turn power management on or off
- * Turn the floppy disk controller and Resume on or off
- * Enable or disable the serial ports
- * Set the hard drive, standby mode, and suspend mode timeouts

To run the power program, follow these steps:

1. Exit any program you are running.
2. If you are not in Drive C, type the following: c:<ENTER>
3. Select the DOS directory by typing the following: cd \dos <ENTER>
4. At the prompt, type the following: power383 <ENTER>

Note: Refer to (Keyboard) Faxback Doc. # 1234 for more information on Power Management using the Functions Key Combinations.

(jej-05/11/94)□