

The SIMM sockets on the main logic board support 32- or 36-bit 1MB, 2MB, 4MB, 8MB, and 16MB SIMMs. The computer requires SIMMs rated at 70 ns or faster.

Memory upgrade SIMM's can be purchased through Third Party products. The 4MB (1x32) SIMM Kit can be ordered under catalog number 250-5138.

NOTE: Only 16MB SIMMs that use 4MB X 4 DRAMs are supported.

The following table lists the number and type of SIMMs required for some popular memory configurations. The default configuration, 4MB is listed first.

Total Memory (MB)	SIZE SIMM INSTALLED (MB)				
	BANK 0	BANK 1	BANK 2	BANK 3	INTERLEAVE MODE
4	4	0	0	0	None
5	4	1	0	0	None
6	4	1	1	0	Two-Way
6	4	2	0	0	None
7	4	1	1	1	Two-Way
7	4	2	1	0	None
8	4	2	1	1	Two-Way
8	4	0	2	2	Two-Way
8	4	4	0	0	Two-Way
8	8	0	0	0	None
9	4	1	2	2	Two-Way
9	4	4	1	0	Two-Way
9	8	1	0	0	None
10	4	2	2	2	Two-Way
10	4	4	1	1	Two-Way
10	4	4	2	0	Two-Way
10	8	0	1	1	Two-Way
10	8	2	0	0	None
11	4	4	2	1	Two-Way

11	8	1	1	1	Two-Way
11	8	2	1	0	None
12	4	4	2	2	Two-Way
12	4	4	4	0	Two-Way
12	8	2	1	1	Two-Way
12	8	0	2	2	Two-Way
12	8	4	0	0	None
13	4	4	4	1	Two-Way
13	8	1	2	2	Two-Way
13	8	4	1	0	None
14	4	4	4	2	Two-Way
14	8	2	2	2	Two-Way
14	8	4	1	1	Two-Way
14	8	4	2	0	None
15	8	4	2	1	None
16	4	4	4	4	Four-Way
16	8	4	2	2	Two-Way
16	8	0	4	4	Two-Way
16	8	8	0	0	Two-Way
16	16	0	0	0	None
17	8	1	4	4	Two-Way
17	8	8	1	0	Two-Way
17	16	1	0	0	None
18	8	2	4	4	Two-Way
18	8	8	1	1	Two-Way
18	8	8	2	0	Two-Way
18	16	1	1	0	Two-Way
18	16	2	0	0	None

19	8	8	1	1	Two-Way
19	16	1	2	1	Two-Way
19	16	2	1	0	None
20	8	4	4	4	Two-Way
20	8	8	2	2	Two-Way
20	8	8	4	0	Two-Way
20	16	2	1	1	Two-Way
20	16	0	2	2	Two-Way
20	16	4	0	0	None
21	8	8	4	1	Two-Way
21	16	1	2	2	Two-Way
21	16	4	1	0	None
22	8	8	4	2	Two-Way
22	16	2	2	2	Two-Way
22	16	4	1	1	Two-Way
22	16	4	2	0	None
23	16	4	2	1	None
24	8	8	4	4	Two-Way
24	8	8	8	0	Two-Way
24	16	4	2	2	Two-Way
24	16	4	4	0	Two-Way
24	16	8	0	0	None
25	8	8	8	1	Two-Way
25	16	4	4	1	Two-Way
25	16	8	1	0	None
26	8	8	8	2	Two-Way
26	16	4	4	2	Two-Way
26	16	8	1	1	Two-Way
26	16	8	2	0	None

27	16	8	2	1	None
28	8	8	8	4	Two-Way
28	16	4	4	4	Two-Way
28	16	8	2	2	Two-Way
28	16	8	4	0	None
29	16	8	4	1	None
30	16	8	4	2	None
32	8	8	8	8	Four-Way
32	16	8	4	4	Two-Way
32	16	0	8	8	Two-Way
32	16	16	0	0	Two-Way
33	16	1	8	8	Two-Way

(smc-12/06/93)